



**AUDIOVOX**  
CORPORATION

## Model AX-200 Installation Manual

### SELECTABLE FEATURES

**Note:** When both Passive Arming and Voltage Sensing are selected, you must hardwire the driver's door pin switch in order to begin the passive arming sequence.

#### RF Programmable Features:

Feature Selection	1 Chirp	2 Chirps	3 Chirps	4 Chirps	Default
1st Door L/UL	1 Sec.	3.5 Sec.	1 Sec L, Dbl. U/L		1 Sec.
2nd Accy Lock	Auto Lock On	Auto Lock Off			Auto Lock Off
3rd Accy. UL	Auto UL Dr.	Auto UL All	Auto UL Off		Auto UL Off
4th Passive Locks	Passive	Active			Active
5th Passive/Active Arm	Passive Arm	Active Arm			Active Arm
6th Voltage Sense	Voltage Sense	Hardwire			Hardwire
7th Siren/Horn	Siren/Horn	Siren Only	Horn Only		Siren/Horn
8th Horn Chirp	10mS	16mS	30mS		16mS
9th Override Method	Custom Code	Valet			Valet
10th Two Step Unlock	On	Off			Off
11th Chirp Delete From Tx	On	Off			Off

#### To program these selectable features;

	Action	System Response
First	Turn ignition on	No response
	Press and release the valet switch 3 times Within 3 seconds, turn ignition Off Then On	1 Chirp - LED 1 flash Short chirp, then long chirp 1 chirp = 1 second door locks 2 chirps = 3.5 second door locks 3 chirps = 1 sec. lock, dbl 1 sec. unlock
	Press transmitter Lock button to change Press transmitter Lock button to change <b>or</b>	
Second	Press and release the valet switch Press transmitter Lock button to change <b>or</b>	2 chirps = auto locks off 1 chirp = auto locks on
	Press and release the valet switch Press transmitter Lock button to change Press transmitter Lock button to change <b>or</b>	3 chirps = auto unlock off 1 chirp = auto unlock dr. 2 chirps = auto unlock all
Fourth	Press and release the valet switch Press transmitter Lock button to change <b>or</b>	2 chirps = active locks 1 chirp = passive locks
	Press and release the valet switch Press transmitter Lock button to change <b>or</b>	2 chirps = active arming 1 chirp = passive arming
Sixth	Press and release the valet switch Press transmitter Lock button to change <b>or</b>	2 chirps = hardwire 1 chirp = voltage sense
	Press and release the valet switch Press transmitter Lock button to change Press transmitter lock button to change	1 chirp = siren and horn output 2 chirps = siren output only 3 chirps = horn output only

	<b>or</b>	
Eight	Press and release the valet switch Press transmitter Lock button to change Press transmitter Lock button to change	2 chirps = horn chirp output 16mS 3 chirps = horn chirp output 30mS 1 chirp = horn chirp output 10 mS
	<b>or</b>	
Ninth	Press and release the valet switch Press transmitter Lock button to change	2 chirps = valet switch override operation 1 chirp = custom code override operation
	<b>or</b>	
Tenth	Press and release the valet switch Press transmitter Lock button to change	2 chirps = 2 step unlock off 1 chirp = 2 step unlock on
	<b>or</b>	
Eleventh	Press and release the valet switch Press transmitter Lock button to change Press and release the valet switch	2 chirps = chirp delete from transmitter inactive 1 chirp = chirp delete from transmitter active Exit program mode
	<b>or</b>	
	Turn ignition key off	Exit program mode

**Note:** Once you enter the feature programming mode, do not allow more than 30 seconds to pass between steps, or the programming will be terminated.

## INSTALLATION OF MAJOR COMPONENTS

### Control Module:

Select a mounting location inside the passenger compartment ( up behind the dash ), and secure using the two screws provided. The control module can also be secured in place using cable ties.

**Do not** mount the control module in the engine compartment, as it is not waterproof. You should also avoid mounting the unit directly onto factory installed electronic components. These components may cause RF interference, which can result in poor transmitter range or intermittent operation.

### Siren:

Select a mounting location in the engine compartment that is well protected from access below the vehicle. Avoid areas near high heat components or moving parts within the engine compartment. To prevent water retention, the front or sounding end of the siren must be pointed downward when mounted.

Mount the siren to the selected location using the screws and bracket provided.

### Hood or Trunk Pin Switch:

A pin switch is included for use in protecting the hood or trunk ( or hatchback ) of the vehicle. The switch must always be mounted to a grounded, metal surface of the vehicle. It is important to select a location where water cannot flow or collect and to avoid all drip gutters on hood and trunk fender walls. Choose locations that are protected by rubber gaskets when the hood or trunk lid is closed.

The pin switch can be mounted using the bracket provided, or direct mounted by drilling a ¼ " diameter mounting hole. Keep in mind that when properly mounted, the plunger of the pin switch should depress at least ¼ " when the hood or trunk lid is closed.

### Dash Mounted LED:

A small LED is included that will serve as a visual indicator of the alarm status. It should be installed in the dash, located where it can be easily seen from outside the vehicle, yet not be distracting to the driver.

Once a location has been selected, check behind the panel for wire routing access and to confirm the drill will not damage any existing components as it passes through the panel.

Drill a ¼ " diameter hole and pass the red and blue wires from the LED through the hole, from the front of the panel. Firmly press the body of the LED into the hole until fully seated.

### Valet Switch:

Select a mounting location for the switch that is easily accessible to the driver of the vehicle. The switch does not have to be concealed, however, concealing the switch is always recommended, as this provides an even higher level of security to the vehicle.

The valet switch can be mounted to the lower side of the dash by drilling a ¼ " diameter hole in the selected location.

Be sure to check behind the dash for adequate clearance for the body of the switch and to confirm that the drill will not damage any existing components as it passes through the dash. You should also make certain that the back of the switch is accessible for wiring later in the installation.

**Shock Sensor:**

Select a solid mounting surface for the shock sensor on the firewall inside the passenger compartment and mount the sensor using the two screws provided. The shock sensor can also be secured to any fixed brace behind the dash using tie straps.

Whichever mounting method is selected, make certain that the sensitivity adjustment is accessible for use later in the installation.

**WIRING THE SYSTEM**

**Large 15 Pin Edge Connector:**

**White Wire: + 12 VDC PULSED PARKING LIGHT OUTPUT ( 15 AMP MAX )**

This wire is provided to flash the vehicle's parking lights. Connect the white wire to the positive side of one of the vehicle's parking lights.

**Red Fused Wire: + 12 VDC CONSTANT BATTERY SOURCE**

This wire controls the sensitivity of the voltage sensing circuit, which detects the turning on of an interior light when a door is opened. It will also detect the switching on of parking or headlamps and in many cases will trigger the alarm when a thermostatically controlled electronic radiator cooling fan switches on.

When installing this system into vehicles with electronic "after fans" , it is recommended you disable the voltage sense circuit.

In voltage sensing applications, the closer to the battery that the red wire is connected, the less sensitive the voltage sense circuitry will be. Moving this connection point to the fuse panel will increase the sensitivity, and connecting to the courtesy lamp fuse in the vehicle will provide maximum sensitivity of the voltage sense circuit.

When hardwiring the control module, the voltage sense circuit must be disabled. After wiring of the control module and connecting the Red wire to a fused battery source, be certain program feature # six is set for Hardwire.

**Red/White Wire: DELAYED 300 mA PULSED OUTPUT / CHANNEL 2**

This wire pulses to ground via an independent RF channel from the keychain transmitter. This is a transistorized, low current output and should only be used to drive an external relay coil.

**WARNING:** Connecting this wire to the high current switched output of trunk release circuits, some remote start trigger inputs, will damage the control module.

Connect this wire to terminal 86 of the AS - 9256 relay (or equivalent 30A automotive relay) and wire the remaining relay contacts to perform the selected function of channel 2.

**Brown Wire: POSITIVE OUTPUT TO SIREN**

Route this wire through a rubber grommet in the firewall, and to the siren location.

Connect the brown wire to the positive wire of the siren. Secure the black ground wire of the siren to chassis ground.

**Black Wire: CHASSIS GROUND**

Connect this wire to a solid, metal part of the vehicle's chassis. Do not confuse this wire with the thin black antenna wire that exits the control module independently.

**Yellow Wire: + 12 VDC IGNITION SOURCE**

Connect this wire to a source that is live when the key is in the on and crank positions. Be sure that this source is off when the key is in the off position.

**Blue Wire: ( - ) INSTANT TRIGGER ZONE**

This is an instant on ground trigger wire. It must be connected to the previously installed hood and trunk pin switches.

**Green Wire: - DOOR TRIGGER**

If the vehicle's courtesy light switches have a ( - ) ground output when the door is opened (GM and most Imports), you must connect this wire to the negative output from one of the door switches.

**WARNING: Do not use the green wire if the vehicle has + 12 volt output type door switches. ( see Purple Wire ).**

Note for vehicles with interior delay lighting see programming under title "Completing The Installation".

**Purple Wire: + DOOR TRIGGER**

If the vehicle's door courtesy light switches have a + 12 volt output when the door is opened ( most Fords and some Imports ), you must connect this wire to the positive output from one of the door switches. In most cases, the purple wire will only need to be connected to one door switch, no matter how many doors the vehicle has.

**WARNING: Do not use the purple wire if the vehicle has ground output type door switches. ( see Green Wire ).**

Note for vehicles with interior delay lighting see programming under title "Completing The Installation".

**Orange Wire: 300 mA GROUND OUTPUT WHEN ARMED - N. C. STARTER DISABLE**

This wire is provided to control the starter cut relay. Connect the orange wire to terminal 86 of the relay. Connect relay terminal 85 to an ignition wire in the vehicle that is live when the key is in the on and crank positions, and off when the key is in the off position. ( This is where the yellow wire from the alarm should be connected ).

Cut the low current starter solenoid wire in the vehicle, and connect one side of the cut wire to relay terminal 87A. Connect the other side of the cut wire to relay terminal 30.

**Note: This is a normally closed starter cut arrangement and when power is removed from the security system, the starter disable feature will not operate, allowing the vehicle to start. The Manufacturer does not recommend using the Orange wire to interrupt anything but the starting circuit of the vehicle.**

**Brown w/Black Trace Wire: LOW CURRENT NEGATIVE HORN OUTPUT (300mA MAX CURRENT)**

This wire provides a 300mA pulsed output to beep the vehicle's horn. This low current pulsed output should only be connected to the low current switched ground output from the vehicle's horn switch. If the vehicle switches high current ground or + 12 volts to the horn, a relay must be used to operate the vehicle horn. Connect the Brown/Black wire to terminal #86 of a VF45F11 P&B or equivalent 30A automotive relay. Connect terminal #85 to a fused + 12 volt source. Connect the remaining relay contacts 87, 87a and 30 to perform the switching function the vehicle's horn circuit requires.

**White w/Green Trace Wire: Activation Output (Dbl. Push Required)**

This wire is controlled from the transmitter button programmed to the receiver's channel 2. By double pressing this the transmitter button, this output will become active for 1 second. This is a transistorized, low current ( 300 mA ) output, designed to provide an output only when the transmitter is intentionally operated, such as is the case with remote start add on modules. If you require more than 300mA drive from this output, you must drive an external relay coil, and arrange the relays contacts to preform the specified function.

**Black w/ White Trace Wire: Entry Illumination ( 300 mA max. )**

This wire provides a 30 second ground signal whenever the system is disarmed, and pulses ground whenever the system is triggered. It should be used to provide the ( optional ) entry lighting and to flash the vehicle's dome light while the alarm is sounding. This is a transistorized, low current output and should only be used to drive an external relay coil.

Connect the black with white trace wire to terminal 86 of the AS - 9256 relay ( or equivalent 30A automotive relay ) and wire the remaining relay contacts according to the polarity of the dome light circuit in the vehicle.

**NOTE: When wiring this feature in vehicles with factory equipped delay lighting circuits, it is best to connect to the output of the timer which feeds the dome light, rather than at the door switch. This will ensure that the dome light pulses when the alarm is triggered.**

**Blue/White Wire:** ( - ) Instant Trigger Zone 1

This is an instant on ground trigger wire. This wire ( zone ) should be reserved for connection to optional ground output trigger devices such as motion and / or shock impact sensors.

**2 Pin Blue Connector:** VALET SWITCH

Route the grey and black wires in the 2 pin connector from the valet switch to the control module, and plug it into the mating blue connector on the side of the module.

**2 Pin White Connector:** DASH MOUNTED LED

Route the red and blue wires in the 2 pin white connector from the LED to the control module, and plug it into the mating white connector on the side of the module.

**4 Pin White Connector:** SHOCK SENSOR

Route the red, black, blue, and green wires in the 4 pin white connector from the shock sensor to the control module, and plug one end into the shock sensor, and the other end into the mating white connector on the side of the module.

**Green / Blue / Blue/Red 3 Pin White Connector:** Door Lock Outputs

These wires will provide either a pulsed ground output to the factory door lock control relay, or a pulsed + 12 volt output to the factory door lock control relay. In either case, the maximum current draw through these outputs must not exceed 300 mA. The Blue/Red wire will provide a pulsed ground only and will only provide an output when the unlock button of the transmitter is pressed a second time after a first unlock command was issued. This is used for second step unlock or all doors unlock in a two step circuit. In this arrangement, Green is used to control the drivers door unlock relay, and the Blue/Red will be used to control unlock of all other doors.

**3 Wire Ground Switched Single Step Door Locks**

In this application, the **green wire** provides a ground pulse during arming, or the **pulsed ground lock** output. Connect the green wire to the wire that provides a low current ground signal from the factory door lock switch to the factory door lock control relay.

The **blue wire** provides a ground pulse during disarming, or the **pulsed ground unlock** output. Connect the blue wire to the wire that provides a low current ground signal from the factory door unlock switch to the factory door lock control relay.

Blue/Red is Not Used.

**3 Wire Ground Switched 2 Step Door Locks**

In this application, the **green wire** provides a ground pulse during arming, or the **pulsed ground lock** output. Connect the green wire to the wire that provides a low current ground signal from the factory door lock switch to the factory door lock control relay.

The **blue wire** provides the first ground pulse during disarming, or the **drivers door pulsed ground unlock** output. Connect this wire to the **drivers door unlock** relay that requires a low current ground signal to unlock only the drivers door. If the vehicle does not have a separate drivers door relay, one will have to be added. Locate the drivers door unlock motor wire and cut it at a convenient location to allow wiring of an optional relay. Connect the door side of the cut wire to terminal 30 of the optional relay added. Connect the vehicle side of the cut wire to terminal 87a of the optional relay added. Connect the blue wire of the 3 pin harness to terminal 86 of the optional relay added. Connect terminal 85 of the optional relay added to a fused constant + 12 volt source. Most vehicles door lock/unlock motor legs rest at ground, and switch +12 volts to the door lock/unlock motor legs for operation, if this is the case in the vehicle you are working on, connect the remaining terminal, 87, to a fused + 12 volt source. In the rare instance that the vehicle door lock/unlock motor legs rest at + 12 volts and switches ground to the door lock/unlock motors, connect the remaining terminal, 87, to chassis ground.

The Blue/Red wire provides a pulse ground output when the unlock button of the transmitter is pressed a second time after disarming. Connect the Blue/Red wire to the wire that provides a low current ground signal from the factory door unlock switch to the factory door lock control relay.

### 3 Wire Positive Switched Door Locks

In this application, the **green wire** provides a positive pulse during disarming, or the **pulsed + 12 volt unlock** output. Connect the green wire to the wire that provides a low current positive signal from the factory door unlock switch to the factory door lock control relay.

The **blue wire** provides a positive pulse during arming, or the **pulsed + 12 volt lock** output. Connect the blue wire to the wire that provides a low current positive signal from the factory door lock switch to the factory door lock control relay.

### 3 Wire Positive Switched 2 Step Door Locks

The **blue wire** provides a positive pulse during arming, or the **pulsed + 12 volt lock** output. Connect the blue wire to the wire that provides a low current positive signal from the factory door lock switch to the factory door lock control relay.

The **green wire** provides a positive pulse during disarming, or the **drivers door pulsed positive unlock** output. Connect this wire to the **drivers door unlock** relay that requires a low current positive signal to unlock only the drivers door. If the vehicle does not have a separate drivers door relay, one will have to be added. Locate the drivers door unlock motor wire and cut it at a convenient location to allow wiring of an optional relay. Connect the door side of the cut wire to terminal 30 of the optional relay added. Connect the vehicle side of the cut wire to terminal 87a of the optional relay added. Connect the green wire of the 3 pin harness to terminal 86 of the optional relay added. Connect terminal 85 of the optional relay added to chassis ground. Most vehicles door lock/unlock motor legs rest at ground, and switch +12 volts to the door lock/unlock motor legs for operation, if this is the case in the vehicle you are working on, connect the remaining terminal, 87, to a fused + 12 volt source. In the rare instance that the vehicle door lock/unlock motor legs rest at + 12 volts and switches ground to the door lock/unlock motors, connect the remaining terminal, 87, to chassis ground.

The Blue/Red wire provides a pulse ground output when the unlock button of the transmitter is pressed a second time after disarming. Because the vehicle you are working on requires a positive pulse from the factory door lock switch to the factory door lock control relay, you will have to add a relay to invert the output polarity of this wire. Connect the Blue/Red wire to terminal 86 of the optional added relay. Connect terminal 85 & 87 to a fuse + 12 volt source. Connect terminal 30 to the low current door unlock wire from the factory door switch to the door unlock control relay.

### Resistive Circuits, As Well As 4 Wire Polarity Reversal and 5 Wire Alternating 12 Volt Door Lock Control Circuits

These applications require the use of additional components which may include relays, fixed resistors, or for convenience, the AS 9159 Door Lock Interface. Refer to the AUDIOVOX Door Lock Wiring Supplement and or the Audiovox fax back service for information on your particular vehicle for properly connecting to these types of circuits.

### COMPLETING THE INSTALLATION

**NOTE:** This unit has the ability to learn the dome light delay time, up to 60 seconds. If the vehicle has delay interior lights, and you wish to avoid three chirp, defect zone, indication normally associated with this type of interior light, we suggest you learn the interior light delay.

To learn the light delay, start with all doors closed:

(1) Use the transmitter to Lock / Unlock / Lock / Unlock / Lock / Unlock / Lock, the system.

The LED turns on solid to confirm the system entered the learn mode.

(2) Immediately open and close the door of the vehicle to initiate the dome delay.

The unit will monitor the door trigger input Positive, (Purple), and Negative, (Brown) when active.

When the dome light turns off, the unit will add 2 seconds then exit the learn mode.

(3) The LED will begin flashing the Armed indication indicating the unit has exited the learn mode and is armed.

**Antenna Wire:** Be sure to extend the thin black antenna wire to its full length and cable tie into place where it cannot be damaged. Avoid wrapping this wire around major, high current wire looms.

**Adjusting the Shock Sensor:** If used, the sensitivity of the pre - detect circuit is automatically set 30% less sensitive than the full trigger circuit.

Using a small screwdriver, gently turn the adjustment screw fully counterclockwise. ( DO NOT over turn this screw. Maximum rotation for this adjustment is 270° ). Close the hood and trunk lids, and arm the alarm. Wait 6 seconds for the accessories trigger zone to stabilize, then firmly strike the rear bumper with the side of a closed fist considering the amount of force required to break a window.

**CAUTION: Never perform this test on the vehicle's glass, as you may break the window.**

Turn the adjustment screw clockwise ( increasing sensitivity ) about ¼ turn and re - test. Repeat this procedure until the alarm sounds. Ultimately, one firm strike to the rear bumper will cause the alarm to emit pre - detect warning tones.

**WARNING!** Setting the sensitivity too high can cause false alarms due to noise vibrations from passing trucks and heavy equipment. To decrease sensitivity, turn the adjustment screw counter clockwise.

**Wire Dressing:** Always wrap the alarm wires in convoluted tubing, or with a spiral wrap of electrical tape. Secure these looms along the routing using cable ties. This will ensure that the alarm wires are not damaged by falling onto hot or sharp moving surfaces in the vehicle.

**Operation:** Take a few moments to check off the appropriate option boxes in the owner's manual, and to fully explain the operation of the system to your customer.

Place the Valet Switch Tag and or the Remote Start Control Switch Tag on their respective switches and point these out to the customer.

#### 15 Pin Main Connector

White	(+) 12 V Parking Light Output
Red	(+) 12 V Constant Power Input 15A
Red/Purple	(+) 12 V Constant Power 5A
Red/White	(-) Trunk Pop Output Pulsed 300mA
Brown	(+) Siren Output
Black	(-) Chassis Ground
Yellow	(+) 12V Ignition Input
Blue	(-) Trunk Pin Instant Trigger Input (Shunted During Trunk Pop)
Green	(-) Door Trigger Input
Purple	(+) Door Trigger Input
Orange	(-) Starter Disable Output / Ground when Armed Output 300mA
Brown/Black	(-) Horn Honk Output 300mA
White/Green	(-) Activation Output (Output With Double Push Of Trunk Pop Button) 300mA
Black/White	(-) Domelight Supervision Output 300mA
Blue/White	(-) Instant Trigger Input

#### 3 Pin Lock Harness

Green	(+) Unlock / (-) Lock 300mA max
Blue	(+) Lock / (-) Unlock 300mA max
Blue/Red	(-) 2nd Unlock 300mA max

